

Bosch Programming Worksheet

For Bosch Solution 880, Bosch Solution 2000 Bosch
Solution 3000



Zone Type Programming Locations

Zone	Programming Location	Value
1	267	Enter a digit between 1-15 from the Zone Type table, depending on the zone type that you need
2	274	
3	281	
4	288	
5	295	
6	302	
7	309	
8	316	

Zone Type Table

Zone Type	Description
0	Instant Zone
1	Handover Zone
2	Entry Delay - Timer 1
3	Entry Delay – Timer 2
4	<<Reserved>>
5	<<Reserved>>
6	24 Hour Medical Alarm
7	24 Hour Panic Alarm
8	24 Hour Hold-Up Alarm
9	24 Hour Tamper Alarm
10	<<Reserved>>
11	Keyswitch Input
12	24 Hour Burglary Alarm
13	24 Hour Fire Alarm
14	Chime Zone
15	Spare Zone

Stay Mode Programming Locations

Zone	Programming Location	Notes
1	271	Enter either a '14' or a '15' in each of the programming locations: 14 = This zone will be ACTIVE in STAY Mode 15 = This zone will be BYPASSED in STAY Mode
2	278	
3	285	
4	292	
5	299	
6	306	
7	313	
8	320	

Delay Timers – Programming Examples

Delay Time Required	Entry Delay – Timer 1		Entry Delay – Timer 2		Exit Delay Timer	
	Programming Locations	Programming Locations	Programming Locations	Programming Locations	Programming Locations	Programming Locations
	466	467	468	469	470	471
10 seconds	10	0	10	0	10	0
20 Seconds	4	1	4	1	4	1
30 Seconds	14	1	14	1	14	1
60 Seconds	12	3	12	3	12	3
90 Seconds	10	5	10	5	10	5